

RADAR 464-02

BSC Filters Limited
10-11 Stirling Park, Bleriot Way
Clifton Moor, York, YO30 4WU. UK
Telephone: +44 (0) 1904 694250
E-mail: sales@bscfilters.com
Web-site: www.bscfilters.com

COMBLINE BANDPASS FILTER

Designed specifically for X Band radars, its high power handling capability, extremely compact size and extended stopbands ensure this filter is ideally suitable for X band transmitters.

Passband:	8.5 to 10.5 GHz
Insertion Loss:	2.0 dB max
Return Loss:	14 dB min
Rejection from 1.0 to 6.0 GHz:	60 dB min
Rejection from 13.0 to 24.0 GHz:	60 dB min
Power Handling:	2 kW peak
Operating temperature:	-20 to 70°C
Connectors:	SMA Female
External Finish:	Matt Black

Outline:

