

RADAR 465-02

BSC Filters Limited
10-11 Stirling Park, Bleriot Way
Clifton Moor, York, YO30 4WU. UK
Telephone: +44 (0) 1904 694250
E-mail: sales@bscfilters.com
Web-site: www.bscfilters.com

COMBLINE BANDPASS FILTER

Designed specifically for X Band radars, extremely compact size and extended stopbands ensure this filter is ideally suitable for X Band radar receivers.

Passband:	8.5 to 10.3 GHz
Insertion Loss:	1.0 dB max
Return Loss:	15 dB min
Rejection from DC to 7.8 GHz:	40 dB min
Rejection from 11.03 to 16.0 GHz:	40 dB min
Power Handling:	2 W max
Operating temperature:	-20 to 50°C
Connectors:	SMA Female
External Finish:	Matt Black

Outline:

