

SATCOM 408-02

BSC Filters Limited
10-11 Stirling Park, Bleriot Way
Clifton Moor, York, YO30 4WU. UK
Telephone: +44 (0) 1904 694250
E-mail: sales@bscfilters.com
Web-site: www.bscfilters.com

Ka BAND TRANSMIT FILTER

Designed to offer minimal insertion loss in the Ka Transmit Band, and high isolation protection for the associated receivers, this filter is designed to be fitted to an external feed arm assembly.

Passband:	17.7 to 21.2 GHz
Insertion Loss:	0.35 dB max
Return Loss:	21 dB min
Rejection from 27.5 GHz to 31.0 GHz:	70 dB min
Power Handling:	5 W max
Operating temperature:	-20 to 50°C
Connectors:	UBR220 Flange PBR220 Flange
External Finish:	Gloss White

Outline:

