

EW 456-01

BSC Filters Limited
10-11 Stirling Park, Bleriot Way
Clifton Moor, York, YO30 4WU. UK
Telephone: +44 (0) 1904 694250
E-mail: sales@bscfilters.com
Web-site: www.bscfilters.com

SUSPENDED SUBSTRATE BANDPASS FILTER

This Ku Band filter is ideal for use in the front end of Ku Band receivers. It also offers good isolation over the entire EW spectrum.

Passband:	13.96 to 18.0 GHz
Insertion Loss:	1.5 dB max
Return Loss:	12 dB min
Rejection from DC to 12.1 GHz:	50 dB min
Rejection from 20.4 to 26.0 GHz:	50 dB min
Power Handling:	+20 dBm max
Operating temperature:	0 to 50°C
Connectors:	SMA Female
External Finish:	Matt Black

Outline:

