

SATCOM 398-01

BSC Filters Limited
10-11 Stirling Park, Bleriot Way
Clifton Moor, York, YO30 4WU. UK
Telephone: +44 (0) 1904 694250
E-mail: sales@bscfilters.com
Web-site: www.bscfilters.com

Ku BAND RECEIVE FILTER

Designed for compact receivers, this combine filter offers low loss and high transmit rejection in a compact package, with coaxial connectors for ease of integration.

Passband:	10.7 to 12.75 GHz
Insertion Loss:	1.0 dB max
Return Loss:	14 dB min
Rejection from 2.0 GHz to 8.5 GHz:	50 dB min
Rejection from 14.5 to 18.0 GHz:	50 dB min
Power Handling:	1 mW max
Operating temperature:	-55 to 50°C
Connectors:	SMA Female
External Finish:	Matt Black

Outline:

